MEGATRON®

TECHNICAL SPECIFICATION:

Series Name	MEGATRON® POWERLENS Set		
Model Number	MT76302	MT76332	MT76342
Color	White	Black	Titan
Lamp Holder		GX53	
Incl. Light Source	LM85800	LM85801	LM85802
Light Source Wattage	4,8W		
Beam Angle	60°		
Total Luminous Flux	460lm		
Energy Efficiency Class Light Source <x></x>		F	
Voltage	220–240V~		
Frequency	50/60 Hz		
IP Rating	IP20		

ATTENTION:

Instant start is allowed.

- The luminaire may only be used with GX53 LED light source!
- The operating temperature of the luminaire is -20° C to +40° C
- Designed for indoor applications.

CLASS I	LED	\triangle	((
			CC
ca.8mm		Replace any cracked protective shield.	

CAUTIONS:

- Read the entire manual carefully before installation and operation.
- Installation or replacement should be performed only by licensed and qualified electricians.
- DO NOT disassemble the inner part of the luminaire. Doing so may result in luminaire damage or malfunction.
- Switch OFF the power source before installation, replacement and cleaning! A Wearing gloves during installation is recommended to ensure the luminaire is kept in the best condition.
- Wearing gloves during installation is recommended to ensure the fundinare is kept in the best condition. Before replacement of the lamp or luminaire, turn it off and allow it to cool down. Heat-resistant gloves are mandatory when handling the luminaire. The manufacturer accepts no liability for any damage resulting from the misuse of the luminaire or from when it is used with inappropriate equipment. Important warning for ground drilling and drilling in walls: before drilling, make sure that there are no gas and water pipes or power lines behind or near the drilling spots. Drilling and mounting should be performed only by qualified personnel. Be sure to pay attention to the condition and material of the ground and walls, as the supplied mounting material is not suitable for all ground and wall types. Please inquire about recommended screws and raw plugs for your ground or wall type and condition. The manufacturer accepts no liability for improper wall raw plug mounting and the herefrom resulting damages.
- This product contains a light source of energy efficiency class <F>.
- Consult your dealer if you have any enquiries.

INSTALLATION: MT76302, MT76332, MT76342



- Switch OFF the power supply
- Drill the 100mm diameter drill hole. 2 3. Using a screwdriver, open the screws of the
- connection box.
- Open the connection box.
- Connect the lamp to the power supply. 5.
- Close the connection box. 6 7
- Screw the screws into the connection box to close it.
- Insert the light source LM85800/ 8 LM85801/LM8502 into the lamp holder.
- 9 Place the recessed LED-Downlight in the drilled hole.
- 10.Turn ON the power supply.



Correct disposal of this product:

This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly, to promote the sustainable reuse of material resources. To return your device, please use the return and collection systems, or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

GB