

Montagehinweise

Spot It Wand- / Deckenleuchte 1-flg., Art.Nr. 407 801 ..

Sie haben ein Qualitätsprodukt „Made in Germany“ erworben. Die Leuchte wurde von unserer Qualitätskontrolle sorgfältig geprüft und hat unser Werk in einwandfreiem Zustand verlassen.

Wenn Sie folgende Hinweise genau beachten, werden Sie lange Zeit Ihre „helle Freude“ an dieser Leuchte haben.

! Beim Betrieb der Leuchte können einzelne Leuchtenteile sehr heiß werden. Um Verbrennungen vorzubeugen, ist jeder Hautkontakt mit diesen Teilen zu vermeiden.
! Die Montage der Leuchte darf nur von einem Elektrofachmann vorgenommen werden.
! Die beiliegenden Dübel und Schrauben eignen sich nur für eine Befestigung an einer Betonwand / -decke. Verwenden Sie bei Hohlkörper-, Gipskarton- und ähnlichen Wänden / Decken geeignetes Befestigungsmaterial.
! Leuchtmittelwechsel ist technisch nicht vorgesehen – Brenndauer der LED ca. 30.000h.
! Bewahren Sie die Montagehinweise nach der Leuchtenmontage gut auf.

Dimmer:

Unsere aktuellen Dimmerempfehlungen finden Sie unter www.escale.de
Download/Dimmerempfehlung oder hier:




Lieferumfang

Wand- / Deckenleuchte cpl.
2 Ersatzmadenschrauben
Befestigungsmaterial; Anschlussklemmen incl. Schutzgehäuse ist bereits anmontiert
Montagehinweis


Wand- / Deckenmontage

Lösen Sie die beiden seitlichen Madenschrauben (4) am Gehäuse - Inbusschlüssel ist der Leuchte beigelegt - und entnehmen Sie die Abdeckung.
Das Isoliergehäuse (1) mit Anschlussklemmen (2) und Isolierschutzschlauch (3) ist bereits an den LED-Versorger über eine Steckverbindung angeschlossen.
Trennen Sie diese Steckverbindung durch auseinanderziehen.
Öffnen Sie das Isoliergehäuse (1), schieben Sie die deckenseitigen Leitungen durch den Schutzschlauch (3) in das Isoliergehäuse (1).
Elektrischen Anschluss tätigen und das Isoliergehäuse (1) wieder verschließen.
Achtung: Deckenseitige Leitungen müssen cpl. mit Schutzschlauch abgedeckt sein – innerhalb des cpl. Leuchtengehäuses dürfen keine einfach isolierten Leitungen liegen!
Befestigen Sie das Leuchtengehäuse (dient gleichzeitig als Bohrschablone) mit den beigelegten Schrauben und Dübeln an der Wand / Decke.
Steckverbindung zwischen LED-Versorger und Deckenanschluss wieder zusammenstecken.
Abdeckung auf das Leuchtengehäuse aufsetzen und mit den Madenschrauben (4) befestigen.



Höheneinstellung Lichtelement

Das Lichtelement ist mit einem 3D-Kipp-Drehgelenk ausgestattet.
Lichtelement bis zum einrasten nach außen ziehen (ca. 2,5 cm) – Lichtelement über das Kipp-Drehgelenk schwenkbar. **Achtung: Den Anschlag nicht überdrehen!**
Durch leichtes drücken – am Druckpunkt über Kipp-Drehgelenk - Lichtelement bis zum einrasten zurückschieben.



Technische Angaben

Netzspannung 230 V AC, 50-60 Hz
Schutzklasse 2
1 x LED 9,6 W - 2700 Kelvin



Korrekte Entsorgung dieses Produkts (Elektromüll)

Stand 06/2017



Mounting Instructions

Spot It wall / ceiling lamp 1-light; Art. no.: 407 801 ..

You bought a quality product "Made in Germany." The lamp was conscientiously tested by quality control and left our factory in faultless condition.

If you strictly follow the instructions below you will be "delighted" with this lamp for a long time.

! While the light fixture is operated some components may become very hot. Please avoid any direct contact with these parts in order to avoid burnings!
! The lamp shall be installed by a skilled electrician only.
! The attached dowels and screws are fit for fastening to concrete walls / ceilings only. Use appropriate fastening material for hollow filler block floors, gypsum board and similar walls / ceilings.
! Lamp replacement is technically not provided – burn time LED about 30.000h.
! Safely keep the mounting instructions after installation of light.

Dimmer:

Our up-to-date dimmer recommendations can be found on our website www.escale.de
Download/Dimmerempfehlung or here:



Scope of supply

Wall / Ceiling lamp complete
2 replacement allen screws
fastening material, terminals incl. safety housing already mounted
mounting instructions

Install to wall / ceiling / power connection

Tighten both lateral allen screws (4) at the housing – allen key attached – and remove the cover.

The insulation housing (1) with terminals (2) and cable protective tube (3) is already mounted to the LED provider by means of a plug-in connection.

Disconnect this plug-in connection.

Open the insulation housing (1), put the cables in the ceiling through the cable protective tube (3) into the insulation housing (1).


Make connection to power supply and close the insulation housing (1) again.

Attention: The cables coming from the ceiling must be covered completely with the protective tube – within the light fixture housing there may not exist any cables only simply insulated.

Fasten the light fixture housing (serves as a template) with the attached screws and plugs to the wall / ceiling.

Re-connect the plug-in connection.

Replace the cover on the housing and fasten it with the allen screws (4).




Adjust height of light element

The light element is equipped with a 3D tilt/swivel joint.

Pull the light element outwards until it locks (ca. 2,5 cm) – light element is rotatable by means of the tilt/swivel joint. **Attention: do not overwind the stop!**

Push back the light element until it snaps into place by slightly pressing directly over the tilt swivel.



Technical Data

Power connection 230 V AC, 50 - 60 Hz
protective standard class 2
1 x LED 9,6 W - 2700 Kelvin



Correct disposal of this product (Waste electrical & electronic equipment)

as at 06/2017