#### Instructions




# Bulb SR1 & Mega Bulb SR2 By Sofie Refer 2006

Congratulations with your new Bulb or Mega bulb lamp, designed in 2006 by Sofie Refer. We hope you will enjoy using this product and follow these instructions to ensure correct installation. If you have any questions or comments, please do not hesitate to contact us by mail on:

info@andtradition.com

### Bulb SR1 & Mega Bulb SR2 By Sofie Refer 2006

Please read these instructions carefully and retain them for future reference to ensure that the product is used correctly. For your own safety, please study each step of this instruction manual first. & Tradition is not responsible for any faults or damages caused by not following these instructions correctly. Do not modify this product in any way.



#### Contents


- A Lamp (1 x lamp included)
- **B** Canopy with metal ceiling bracket
- C Connection box

#### Tools needed

- Flat head screwdriver
- Bulb type E27








- The lamp is only intended for interior use.
- Consult a professionally qualified electrician if in any doubt.
- Do not place the cable within reach of small children or anywhere there is a risk of falling over it.
- Disconnect the electricity supply at the fuse box, before commencing work.

#### Cleaning instructions

- Wipe surface of lamp shade with a soft, damp sponge or cloth.
- Do not use any abrasive cleaning tools such as steel wool, scouring sponges or stiff brushes.
- Never use strong cleaning agents such as white spirit, terpentine, household glass cleaner or cellulose thinners.
- Only wipe the inside of the shade with a soft, damp cloth or feather duster.




#### Step 1

Ensure power supply is turned off and remove any existing lamp fitting.


Locate the supply cable and ensure it is ready to be fitted to the connector box.

Mount the metal bracket (B) securely in the ceiling with screws and wall plugs, appropriate for the ceiling of installation.



#### Step 2


To determine the right suspension height for the lamp, pass the electrical cord through the strain relief of the metal bracket. (B) When you have the desired suspension height of the lamp, tighten the plastic screw of the strain relief.



#### Step 3


#### Connecting the wires:

Pass the supply cable though the isolation sleeve Cut off the excess cord so that a minimum of 80 mm cord is left to reconnect to the cable connector. Peel back the outer cable to expose 30 mm of the blue and brown inner cables. Strip the inner cable to expose 5 mm of wire. Connect the blue supply wire (N) to the terminal of the connector marked 'N'. Connect the brown supply wire (L)to the terminal of the connector marked 'L'.



#### Step 4

Shut the connection box closed, and install the plastic canopy onto the metal plate



Step 5
Install the light bulb.

## &Tradition®