

NEMO

Luminaire

Code ADM EWW 31
Name App. de Marseille 2x8W

Measurement

Code adm112018
Name App. de Marseille 2x8W

Luminaire Flux	926.20 lm	Luminaire Power	16.00 W	Efficacy	57.89 lm/W	Efficiency	100.00%
Lamps Flux	926.20 lm	Maximum value	256.88 cd/klm	Position	C=0.00 G=0.00	CG	Double Symmetrical
Rectangular Luminaire Round Luminous Area	Length Diam.	280 mm 170 mm	Width Height	170 mm 0 mm	Height	395 mm	
Horizontal Luminous Area Emitting area on Plane 0° Emitting area on Plane 90°	0.022698 m2 0.000000 m2 0.000000 m2	Emitting area on Plane 180° Emitting area on Plane 270° Glare area at 76°	0.000000 m2 0.000000 m2 0.005491 m2				
Coordinate system Date Measurement Distance	CG 27-01-2000 0.00	Symmetry Type Maximum Gamma Angle Measurement Flux	Double Symmetrical 180 926.20 lm				
Operator Temperature Humidity Notes	25.00 °C 60.00 %	Source Voltage [V] Source current [A] Photocell	230.00 V				

Line	Code	Luminaire Lamps Name	Flux [lm]	Pow. [W]	Q.ty
	Led E27 A60	Led E27 A60	926.20	16.00	1
C.I.E.	67 92 98 46 100	D DIN 5040	C52		
F UTE	0.46 C + 0.54 T	B NBN	BZ 2		

